



Specifications

MD1818PUX – Large Format Powered Analogue Live Mixer

Mixer Type	Powered, Large Format Analogue Live Mixer
Mono Input Channels	12 × XLR and 1/4" Jack (Line)
Mono Channel Features	Independent rotary Gain, 60mm Level Faders
Compression	Compression available on 6 mono channels
Stereo Input Channels	2 × 1/4" Jack
Stereo Channel Features	60mm Level Faders
Channel EQ	3-Band Rotary (Low, Mid, High)
Mono Channel Controls	Low-cut Switch, Pan, Effects 1&2 Send, Aux Send, Signal LED, Peak LED, PFL Switch, Sub-group Switch, Main Switch
Stereo Channel Controls	-10dB Switch, Balance, Aux Send, Signal LED, Peak LED, PFL Switch, Sub-group Switch, Main Switch
MP3 Media Player	USB Port (Play & Record)
Built-in Effects	2 × 16 DSP Effects Processors
Effects Channel Controls	2 × 60mm Effects Faders, Repeat Controls, Effects Send Controls
Master Channel EQ	9-Band Graphic Equaliser
Master Channel Controls	L&R Main 60mm Faders, Subgroup 1&2 60mm Faders, Aux 60mm Fader, Headphone Volume (rotary), 2 Track/MP3 Volume, Quad 12-LED Level Meter, Assignable 48V Phantom Switches (per channel bank)
Line Outputs	1/4" Jack
Powered Output 1	NL4: 2 × 600W RMS @ 4Ω (Both Channels Driven, Max Load per Channel: 4Ω)
Powered Output 2	NL4: 2 × 300W RMS @ 4Ω (Both Channels Driven, Max Load per Channel: 4Ω)